



Portable Petrol Generator Model:SRGE6500D

- 4 Stage Digital Meter Display (Voltage / Frequency / Hours / Oil)
- Push Start Button / Electric Start
- Battery On / Off Switch
- Automatic Voltage Regulator
- Low Oil Alert Sensor
- Pure Copper Alternator with Advanced Wind Design
- 25L Large Capacity Fuel Tank
- Large Muffler Design to Reduce Exhaust Noise
- Compact and Safe Design with Rugged 25mm Frame
- Robust Wheels and Convenient Foldable Handles
- Tank Protector

Customer Model:	SRGE6500D
FTY Model:	CBSGE6500E
Frequency :	50Hz
Rated Voltage:	230V
Rated Current:	21.7A
Max AC Output at level:	5500W
Power Factor:	1
Net Weight:	82.2 kg
Performance Class:	G1
Engine:	CBS420F(420cc)
Rated Speed:	3000rpm
Protection Grade:	IP23M

